



PASSION-RADIO.FR

Analogique - Numérique - SDR

受信用分配器/混合器

**SPLITTER
& COMBINER**

SS500

The SS500 is a splitter & combiner to connect one antenna with two receiving machines at the frequency range 0.5-500MHz. This product also can be used one receiving machine with two antennas.

■ 定 格

周波数	0.5~500MHz
アイソレーション	0.5~3MHz 18dB以上 3~200MHz 30dB以上 200~500MHz 17dB以上
挿入損失	0.5~3MHz 0.6dB以下 3~200MHz 0.8dB以下 200~500MHz 1.0dB以下
インピーダンス	50Ω
V S W R	2.0以下
コネクタ	M-J型
本体外形寸法	46(W)x27(H)x57(D)mm
重量	130g

■ SPECIFICATIONS

Frequency	0.5~500MHz
Isolation	0.5~3MHz More than 18dB 3~200MHz More than 30dB 200~500MHz More than 17dB
Loss	0.5~3MHz Less than 0.6dB 3~200MHz Less than 0.8dB 200~500MHz Less than 1.0dB
Impedance	50ohms
VSWR	Less than 2.0
Connector	S0-239
Dimensions	46(W)x27(H)x57(D)mm
Weights	130g

Caution

1. If using the SS500 as a combiner, please make sure to connect two antennas. If using one antenna only, please connect to a dummy load.
2. The SS500 is designed for indoor or mobile use. Do not use it outdoor.
3. The SS500 is for receiving only. Do not transmit.

● Though these products are manufactured under strict quality control, if damage is caused by transporting, ask your dealer promptly.

● Design and specifications of these products will be changed for future improvement without advance notice.

DIAMOND ANTENNA CORPORATION

Website <http://www.diamond-ant.co.jp/english/>

Miyata Building, No. 15-1, 1-chome Sugamo, Toshima-ku Tokyo, Japan 170-0002

Phone. +81-3-3947-1411 FAX. +81-3-3944-2981