

ICOM

VHF/UHF DUAL BAND  
FM TRANSCEIVER

IC-P7A

## The Go-Anywhere, Mini Dual Bander!

- Ultra compact, lightweight body  
—47×81×28 mm\*, 160g\*\*  
\* 1<sup>27</sup>/<sub>32</sub>×3<sup>3</sup>/<sub>16</sub>×1<sup>3</sup>/<sub>32</sub> in, projections are not included.  
\*\* 5.6oz, including BP-243 and antenna
- 20 hours of operating time\* or  
15 hours of continuous TV/FM receive capability  
with slim Lithium-Ion battery pack  
\* Tx:Rx:Stand-by=5:5:90 with power save on




- Wideband receiver (0.495–999.990MHz\*)  
allows you to listen to FM, TV (audio)  
broadcasts and other service  
communications

\* Receiver range differs depending on version

- VHF/UHF dual bander with 1.5W/1.0W  
output power (One band at a time)
- CTCSS and DTCS tone for  
repeater access and quiet stand-by
- Minimum number of buttons for  
simple operation
- 1000 alphanumeric memory channels  
with flexible memory bank system
- Supplied rapid charger, BC-164, charges  
the battery pack in 3 hours (approx.)



### compact body & stylish design



Icom Inc.

Other features

- Auto memory write scan stores detected busy channels in the auto memory write bank, and you can transfer them to the regular memory channels.
- Bank link scan allows you to detect busy channels from the selected banks.
- The pocket beep alerts the operator with a beep sound when the transceiver receives a signal containing a preset tone.
- Large backlit LCD with backlit buttons for night time operation
- Priority watch with priority beep • Auto squelch • 10dB attenuator • Auto power off
- Auto power save • Tone scan • Auto repeater function\* (\* Depending on version)
- Weather channel receive with weather alert\* (\* USA version only)



SPECIFICATIONS

GENERAL

• Frequency coverage : (Unit: MHz)		
Version	Tx working range	Rx working range
U.S.A.	144-148,430-450**	0.495-999.990**1*2
Canada	144-148,430-450**	0.495-999.990**
Australia	144-148,420-450**3	0.495-999.990**3
General	136-173.995, 400-478.995**	0.495-999.990**3

\*1 Guaranteed range, 144-148, 440-450MHz \*\* Cellular blocked  
 \*\*3 Guaranteed range, 144-148, 430-440MHz

• Mode	: FM, AM*, WFM*	*RX only
• No. of memory channels	: 1252 (1000 regular, 2 call, 50 scan edges and 200 auto memory write)	
• Antenna impedance	: 50Ω (SMA)	
• Power supply requirement	: 3.7V DC (With specified battery pack)	
• Usable temperature range	: -10°C to +60°C; +14°F to +140°F	
• Frequency stability	: ±6ppm (-10°C to +60°C)	
• Tuning step increments	: 5, 6.25, 8.33, 9, 10, 12.5, 15, 20, 25, 30, 50, 100, 200kHz	
• Current drain (at 3.7V DC, approx.):		
Transmit	High (VHF/UHF) 1.5A/1.5A	
Low (VHF/UHF)	0.4A/0.5A	
Receive	Stand-by 80mA	
Max. audio	150mA	

- Dimensions (W×H×D) : 47×81×28mm; 1<sup>7</sup>/<sub>8</sub>×3<sup>1</sup>/<sub>8</sub>×1<sup>1</sup>/<sub>2</sub> in (Projections not included)
- Weight (approx.) : 160g; 5.6oz (with BP-243 and ANT)
- Ext. MIC/SP connector : 4-conductor 3.5 (d) mm (1/8") /2kΩ/8Ω

- Spurious rejection ratio : More than 40dB
- Audio output (at 3.7V DC) : More than 50mW at 10% distortion with an 8Ω load

TRANSMITTER

- Output power VHF : High 1.5W, Low 0.1W (approx.)
- UHF : High 1.0W, Low 0.1W (approx.)
- Max. frequency deviation : ±5.0kHz
- Spurious emissions : Less than -60dB

RECEIVER

- Intermediate frequencies : 46.35MHz, 450kHz (AM/FM)  
14.85MHz, 450kHz (WFM)
- Sensitivity (at 12dB SINAD) : Less than 0.18μV (144/430MHz ham band only)
- Squelch sensitivity : Less than 0.18μV (at threshold; 144/430MHz ham band only)
- Selectivity AM/FM : More than 12kHz at -6dB  
Less than 30kHz at -60dB  
More than 150kHz at -10dB  
Less than 700kHz at -20dB

- Sensitivity (Wideband receiver general):
- FM (at 12dB SINAD)
- 30-89.995MHz : Less than 0.45μV
- 90-143.995MHz : Less than 0.2μV
- 144-147.995MHz : Less than 0.18μV
- 148-179.995MHz : Less than 0.2μV
- 350-470MHz : 0.18μV typ.
- 600-939.990MHz : Less than 1.4μV
- 940-999.990MHz : Less than 2.5μV
- WFM (at 12dB SINAD) : Less than 1.8μV
- 76-107.995MHz : Less than 2.5μV
- 600-799.990MHz : Less than 2.5μV
- AM (at 10dB S/N)
- 0.495-4.995MHz : Less than 2.2μV
- 5.00-29.995MHz : Less than 1.4μV
- 118-136.995MHz : Less than 1.4μV

All stated specifications are subject to change without notice or obligation.

**Supplied accessories:** (\* Depending on version)  
 • Battery pack, BP-243 • Battery charger, BC-164  
 • AC adapter, BC-145LA/LE/LV\* • Antenna • Hand strap

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.

BP-243 BATTERY PACK



3.7V/1800mA Li-Ion battery pack. Same as supplied.

BC-164 RAPID BATTERY CHARGER +BC-145LA/LE/LV AC ADAPTER



Charges the BP-243 in 3 hours (approx). L-shaped plug AC adapter is supplied with the charger, depending on version.

CP-211R CIGARETTE LIGHTER CABLE WITH NOISE FILTER



For use of the BC-164 in a vehicle. (12-16V DC required.)

LC-161 CARRYING CASE



Allows you to put the transceiver on your belt.

AD-92SMA ANTENNA CONNECTOR ADAPTOR



Allows connection of a BNC type antenna.

• CS-P7 CLONING SOFTWARE + OPC-478, OPC-478U CLONING CABLES

For quick and easy programming of memory channels from a PC. (Microsoft® Windows® 98/SE/Me /2000/XP).  
 OPC-478: RS-232C cable, OPC-478U: USB cable

• OPC-474 CLONING CABLE

For transceiver to transceiver cloning.

Microsoft and Windows are registered trademarks of Microsoft Corporation in the U.S.A. and other countries.

HM-153P EARPHONE MICROPHONE



1 plug type microphone that attaches to your lapel, neck-tie, etc.

HM-131 SPEAKER MICROPHONE



Compact and durable body. Equipped with an earphone jack. OPC-782 is required.

HM-128 EARPHONE MICROPHONE



Light weight lapel clip microphone with earphone. OPC-782 is required.

SP-13 EARPHONE



Provides clear audio in noisy environments. OPC-782 is required.

OPC-782 PLUG ADAPTOR CABLE



MIC/SP plug adaptor. For use of the HM-131, HM-128 and SP-13.

Icom Inc.

1-1-32, Kamiminami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013 URL: <http://www.icom.co.jp/world/index.html>

Count on us!

Icom America Inc.

2380 116th Avenue NE, Bellevue, WA 98004, U.S.A.  
 Phone: +1 (425) 454-8155  
 Fax: +1 (425) 454-1509  
 E-mail: [sales@icomamerica.com](mailto:sales@icomamerica.com)  
 URL: <http://www.icomamerica.com>

Icom New Zealand

146A Harris Road, East Tamaki, Auckland, New Zealand  
 Phone: +64 (09) 274 4062  
 Fax: +64 (09) 274 4708  
 E-mail: [inquiries@icom.co.nz](mailto:inquiries@icom.co.nz)  
 URL: <http://www.icom.co.nz>

Icom (UK) Ltd.

Unit 9, Sea St., Herne Bay, Kent, CT6 8LD, U.K.  
 Phone: +44 (0)1227 741741  
 Fax: +44 (0)1227 741742  
 E-mail: [info@icomuk.co.uk](mailto:info@icomuk.co.uk)  
 URL: <http://www.icomuk.co.uk>

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road, Taipei, Taiwan, R.O.C.  
 Phone: +886 (02) 2559 1899  
 Fax: +886 (02) 2559 1874  
 E-mail: [sales@asia-icom.com](mailto:sales@asia-icom.com)  
 URL: <http://www.asia-icom.com>

Your local distributor/dealer:

Icom Canada

Glenwood Centre #150-6165 Highway 17, Delta, B.C., V4K 5B8, Canada  
 Phone: +1 (604) 952-4266  
 Fax: +1 (604) 952-0090  
 E-mail: [info@icomcanada.com](mailto:info@icomcanada.com)  
 URL: <http://www.icomcanada.com>

Icom (Europe) GmbH

Communication Equipment Himmelgeister Str. 100, D-40225 Düsseldorf, Germany  
 Phone: +49 (0211) 346047  
 Fax: +49 (0211) 333639  
 E-mail: [info@icomeurope.com](mailto:info@icomeurope.com)  
 URL: <http://www.icomeurope.com>

Icom France Sa

Zac de la Plaine, 1, Rue Brindejone des Moulinais BP 5804, 31505 Toulouse Cedex, France  
 Phone: +33 (5) 61 36 03 03  
 Fax: +33 (5) 61 36 03 00  
 E-mail: [icom@icom-france.com](mailto:icom@icom-france.com)  
 URL: <http://www.icom-france.com>

Beijing Icom Ltd.

10C07, Long Silver Mansion, No.88, Yong Ding Road, Haidian District, Beijing, 100039, China  
 Phone: +86 (010) 5889 5391/5392/5393  
 Fax: +86 (010) 5889 5395  
 E-mail: [bjicom@bjicom.com](mailto:bjicom@bjicom.com)  
 URL: <http://www.bjicom.com>

Icom (Australia) Pty. Ltd.


A.B.N. 88 006 092 575  
 Unit 1 / 103 Garden Road, Clayton VIC 3168 Australia  
 Phone: +61 (03) 9549 7500  
 Fax: +61 (03) 9549 7505  
 E-mail: [sales@icom.net.au](mailto:sales@icom.net.au)  
 URL: <http://www.icom.net.au>

Icom Spain S.L.

Ctra. de Gracia a Manresa Km. 14,750 08190 Sant Cugat del Valles Barcelona, Spain  
 Phone: +34 (93) 589 26 70  
 Fax: +34 (93) 589 04 46  
 E-mail: [icom@icomspain.com](mailto:icom@icomspain.com)  
 URL: <http://www.icomspain.com>

Icom Polska

Sopot, 3 maja 54, Poland  
 Phone: +48 (58) 550 7135  
 Fax: +48 (58) 551 0484  
 E-mail: [icompolska@icompolska.com.pl](mailto:icompolska@icompolska.com.pl)  
 URL: <http://www.icompolska.com.pl>



Icom Inc. (Japan), is an ISO 9001 and ISO 14001 certification acquired company.