

ICOM

IC-Q7A (U.S.A. version)

IC-Q7E (Europe version)

Meets
MIL-STD 810

Dual band transceiver with wide band receiver

Wide band receive capability—30 to 1300 MHz

The IC-Q7A/E is a mini-power* dual band transceiver with a wide band receiver. The built-in receiver covers a wide frequency range from 30 to 1300 MHz** in FM, AM and WFM modes. This allows you to listen to the air band, TV and FM broadcast stations, the 50 MHz and 1200 MHz amateur bands and more—similar to what a dedicated wide band scanning receiver offers.

* At 3.0 V DC: 350 mW typical for VHF, 300 mW typical for UHF.

**Some frequency ranges may be restricted depending on version.

Ultra compact, drip-resistant body

The transceiver's tiny body measures only 58(W) × 86(H) × 27(D) mm*—easily fitting in your palm or shirt pocket. And drip-resistant construction helps protect the transceiver in bad weather or when operating near the water.

*2³/₃₂(W) × 3³/₈(H) × 1¹/₁₆(D) in.

Tone squelch standard

Tone squelch operation provides quiet standby—only calls directed to you can open the squelch and be heard. 50 tone frequencies are available and in addition a tone scan function is provided.

Large built-in speaker

A large (36 mm: 1¹³/₃₂" diameter) speaker is built-in to the front panel of the IC-Q7A/E providing loud, crystal clear audio even in noisy environments, etc.

Economical design

Only 2 alkaline or Ni-Cd cells are needed. Total driving current has been reduced for longer battery life. Put this together and you have economical, lightweight operation.

Simple operation

The IC-Q7A/E employs an easy band switching system. When you want to change between operating bands, simply push the large band change switch. Controls have been kept to a minimum (8 switches plus power switch and dial) to ensure quick and easy access to all functions.

Automatic squelch

The automatic squelch system detects receive signal strength and adjusts the squelch level accordingly. Manual squelch can also be selected.

Other features

- LCD backlighting with timer
- Automatic repeater function (U.S.A. version only)
- 200 memory channels
- RIT function
- and more

Icom Inc.

SPECIFICATIONS

GENERAL

• Frequency coverage : (unit: MHz)

| | Transmit | Receive |
|--------|--------------------|-------------------------------|
| USA | 144-148 | 30-823.995 |
| | 430-450** | 849-868.995 894-1309.995** |
| Europe | 144-146 430-440 | 30-1309.995** |
| Italy | 144-148 430-440 | 30-1309.995** |
| Asia | 144-148 430-440 | 30-1309.995** |
| USA-1 | 144-148 440-450 | 30-1309.995** |

**Guaranteed 440-450 MHz

*Specifications guaranteed 30-1300 MHz.

- Mode : FM, AM, *WFM* (*Rx only)
- No. of memory ch. : 200
- Usable temp. range : -10°C to +60°C;
+14°F to +140°F
- Tuning steps : 5, 6.25, 10, 12.5, 15, 20, 25,
30, 50 and 100 kHz
- Frequency stability : ±6 ppm (-10°C to +60°C)
- Power supply requirement:
2 × AA(R6) Ni-Cd or alkaline
cells (negative ground)
- Current drain (VHF/UHF; at 3.0 V DC):
Tx max. power 440 mA/380 mA (typical)
Rx rated audio 170 mA (typical)
standby 95 mA (typical)
power saved 38 mA (typical)
- Antenna connector : SMA (50 Ω)

- Dimensions : 58(W)×86(H)×27(D) mm;
(projections not included) 2³/₃₂(W)×3³/₁₆(H)×1¹/₁₆(D) in
- Weight : 170 g; 6 oz (w/ant. and battery)
- MIC/SP connector : 4-conductor 3.5 (d) mm (1/8");
2 kΩ/8 Ω

TRANSMITTER

- Output power : 350 mW typ. (VHF)
(at 3.0 V DC) 300 mW typ. (UHF)
- Spurious emissions : Less than -40 dB*
*-60 dB for Europe and Italy versions.
- Max. freq. deviation : ±5 kHz

RECEIVER

- Receiver system : Triple conversion
superheterodyne
- Intermediate freq. : 1st 266.7 MHz
2nd 19.65 MHz
3rd 450 kHz
- Sensitivity (except spurious points; typical values):
FM 30-117.995 MHz 0.32 μV
(at 12 dB SINAD) 118-174.995 MHz 0.16 μV
175-246.995 MHz 0.22 μV
247-329.995 MHz 0.4 μV
330-379.995 MHz 0.32 μV
380-469.995 MHz 0.18 μV
470-749.995 MHz 1.0 μV
750-999.995 MHz 0.32 μV
1000-1199.995 MHz 0.79 μV
1200-1300 MHz 0.5 μV

- WFM 76-108.0 MHz 1.0 μV
(at 12 dB SINAD) 175-221.995 MHz 1.0 μV
470-770 MHz 5.6 μV
- AM 118-136.0 MHz 0.56 μV
(at 10 dB S/N) 222-246.995 MHz 0.79 μV
247-329.995 MHz 1.4 μV

- Squelch sensitivity : 0.18 μV (144-148 MHz)
0.22 μV (430-450 MHz)
- Selectivity :
FM, AM More than 15 kHz/-6 dB
Less than 30 kHz/-60 dB
WFM More than 150 kHz/-6 dB
- Image rejection ratio : More than 60 dB
(amateur bands only)
- Audio output power : 100 mW typ. at 10% distortion
(at 3.0 V DC) with an 8 Ω load

The IC-Q7A/E meet MIL-STD requirements and strict environmental standards for shock (MIL 810C, D, E) and vibration (MIL 810C, D, E).

Supplied accessories

- Antenna
- Belt clip
- Hand strap

All stated specifications are subject to change without notice or obligations.


OPTIONS

BC-127
Ni-Cd CHARGER

Charges supplied 2 AA (R6) 700 mAh Ni-Cd cells simultaneously in 7 hours. Up to 4 cells can be charged.

LC-146
CARRYING CASE

Helps protect the transceiver from scratches, etc.

HS-85
HEADSET

Allows you hands-free operation. Includes VOX, PTT, "one-touch PTT" (TOT). OPC-782 is additionally required.

HM-46
SPEAKER-
MICROPHONE

Compact and lightweight. Equipped with an ear-phone jack. OPC-782 is additionally required.

SP-13
EARPHONE

Provides clear audio in noisy environments. OPC-782 is additionally required.

OPC-782
PLUG ADAPTER
CABLE

Allows connection between a transceiver and speaker-microphone, headset, etc.

Icom Inc. 6-9-16, Kamihigashi, Hirano-ku, Osaka 547-0002, Japan Phone: 06 6793 5302 Fax: 06 6793 0013

Count on us!

Icom America Inc.

<Corporate Headquarters>
2380 116th Avenue N.E., Bellevue, WA 98004, U.S.A.
Phone: (425) 454 8155 Fax: (425) 454 1509
URL: <http://www.icomamerica.com>
<Customer Service>
Phone: (425) 454 7619

Icom Canada

A Division of Icom America Inc.
3071 #5 Road, Unit 9, Richmond, B.C., V6X 2T4, Canada
Phone: (604) 273-7400 Fax: (604) 273-1900

Icom (Australia) Pty. Ltd.

A.C.N. 006 092 575
290-294 Albert Street, Brunswick, Victoria, 3056 Australia
Phone: 03 9387 0665 Fax: 03 9387 0622
URL: <http://www.icom.net.au>

Asia Icom Inc.

#F No. 68, Sec. 1, Cheng-Teh Road, Taipei, Taiwan R.O.C.
Phone: (02) 2559 1699 Fax: (02) 2559 1673

Icom (Europe) GmbH

Communication Equipment
Himmelfeier Str. 100, D-40225 Düsseldorf, Germany
Phone: (0211) 346047 Fax: (0211) 333639
URL: <http://www.icomeurope.com>

Icom Spain S.L.

Ctra. de Gracia a Marresa Km. 14,750
06190 Sant Cugat del Valles Barcelona, SPAIN
Phone: (033) 589 46 82 Fax: (033) 589 34 46
URL: <http://www.icomspain.com>

Icom (UK) Ltd.

Unit 9, Sea St., Herne Bay, Kent, CT6 8LU, U.K.
Phone: (01227) 741741 Fax: (01227) 741742
URL: <http://www.icomuk.co.uk>

Icom France S.a

Zac de la Plaine, Rue Bénédict des Moulins
BP 5894, 31505 Toulouse Cedex, France
Phone: (561) 36 03 03 Fax: (561) 36 03 00
URL: <http://www.icom-france.com>



Certificate Number 014199

Icom Inc. (Japan), is an ISO9001 certification acquired company.

Your local distributor/dealer: