



ICOM

VHF FM TRANSCEIVER

IC-V85

(U.S.A. Version)

IC-V85E

(Europe Version)

**Compact, and
7W of
power!**

Compact body

While the IC-V85/E provides a full 7 watts of output power, its 110mm* body height is compact enough to allow for easy carrying.

* 4¹/₂ in (projections are not included)

7W of high output power

Let the power of 7 watts extend your communications range. With its large capacity Lithium-Ion battery pack, BP-227, the IC-V85/E provides a practical 7 hours* of operating time. Reduced power (4W/0.5W) settings are also available for even longer operating time.

* Typical operation with Tx: Rx: standby=1:1:8.

External DC power jack

An external DC power jack allows for operation when used with the external DC power supply (11.0V DC). Your IC-V85/E receives and transmits as it charges.



DC power jack

Water resistant construction

The water resistant construction, equivalent to IPX4 rating, provides reliable operation in wet conditions for practical outdoor usage.

107 memory channels and 10 memory banks

Up to 107 memory channels can be stored. Use the 5-character display capabilities to assign your own individual channel names, then store those channels in any of the 10 memory banks. The DMS (Dynamic Memory Scan) system allows you to scan selected memory banks by simply adding and deleting bank links.

Built-in CTCSS/DTCS

Built-in CTCSS/DTCS tone codes provide quiet stand-by and allows you to use tone-access repeaters. The pocket beep alerts you when a matching tone frequency is received. The tone scan detects the tone frequency used in the received signal.

DTMF memory and optional DTMF decoder


16 DTMF memory channels with up to 24 DTMF codes enable you to perform remote control operation. The optional DTMF decoder unit, UT-108, provides code squelch operation and pager function.

Other features

- Weather channel receive with weather alert* (* USA version only)
- Automatic repeater function* (*USA version only)
- Reversible control knob and up/down button assignment



Water resistance, equivalent to IPX4



Backlit LCD and keypad



SPECIFICATIONS

GENERAL

• Frequency coverage (unit : MHz):

Version	Tx	Rx (Working range)
USA	144-148	136-174*1
Europe, UK	144-146	136-174*2

Guaranteed range *1 144-148MHz, *2 144-146MHz

- Mode : FM
- No. of memory Ch. : 107 (incl. 6 scan edges and 1 call)
- Operating Temp. range : -10°C to +60°C ; +14°F to +140°F
- Frequency stability : ±2.5ppm (-10°C to +60°C)
- Power supply : BP-226/BP-227 or requirement 11.0V ± 15% (External DC in)
- Current drain (at 7.2V DC):
 - Tx High (7W) : 2.6A
 - Rx Max. audio : 250mA
 - Stand-by : 80mA
 - Power save : 30mA

- Antenna impedance : 50Ω (BNC)
- Dimensions (W×H×D) : 56 × 110 × 34.4 mm; (Projections not included) 27/32 × 4 1/8 × 1 1/8 in
- Weight (approx.) : 310g; 12.5oz (with BP-227 and Ant.)

TRANSMITTER

- Output power (at 7.2V) : 7.0/4.0/0.5W (High/mid/low)
- Spurious emissions : Less than -60dBc
- Max. freq. deviation : ±5.0kHz
- External microphone connector : 3-conductor 2.5(d)mm (1/16") /2.2kΩ

RECEIVER

- Intermediate freq. : 46.35MHz/450kHz (1st/2nd)
- Sensitivity : Less than 0.2μV (at 12dB SINAD)
- Squelch sensitivity : Less than 0.16μV (threshold)
- Selectivity : More than 55dB
- Spurious and image rejection : More than 60dB
- Intermodulation : More than 55dB
- Audio output power : More than 300mW with an 8Ω load
- Ext. speaker connector : 3-conductor 3.5(d) mm (1/8")/8Ω

Supplied accessories (*Not supplied with some versions)

- Battery case or battery pack*
- Wall charger*
- Antenna
- Belt clip
- Hand strap

All stated specifications are subject to change without notice or obligation.

OPTIONS

BATTERY PACK AND CASE



BP-226 BP-227

BP-226 BATTERY CASE
AA (LR6)×5 alkaline cells.
BP-227 Li-Ion BATTERY PACK
7.2V/1700mAh. Provides 7 hours operating time* (approx.).
* Tx: Rx: standby=1:1:8.

RAPID CHARGER



BC-119N BC-119N+AD-100

BC-119N DESKTOP CHARGER + AD-100 CHARGER ADAPTER + BC-145A/E/V AC ADAPTER
Rapidly charges the BP-227 in 2-2.5 hours. (approx.)

MULTI-CHARGER



BC-121N+AD-100 (6 pcs.) BC-157

BC-121N MULTI-CHARGER + AD-100 CHARGER ADAPTER + BC-157 AC ADAPTER
Rapidly charges up to 6 battery packs (Six AD-100s are required) in 2-2.5 hours.

CIGARETTE LIGHTER CABLE



CP-19R : Cigarette lighter cable with DC-DC converter. 11.7- 15.9V DC required.

CARRYING CASE



LC-167 : Helps protect the transceiver from scratches, etc.

SPEAKER-MICROPHONES




HM-75A : Allows you to remotely select operating channels, etc.
HM-158L : Compact and durable body with screw-type connector.
HM-159L : Full size durable speaker microphone.
HM-153L : Durable earphone-microphone.
HM-128L : Light weight and compact earphone-microphone.

HEADSETS AND PTT/VOX UNIT



HS-94 : Earhook headset with flexible boom microphone.
HS-95 : Behind-the-head headset with flexible boom microphone.
VS-1L : PTT/VOX unit. Required when using HS-94 or HS-95 with the transceiver.
HS-85 : For hands-free operation. Includes VOX, PTT and "one-touch" PTT with a time-out timer.

DTMF DECODER



UT-108 : Provides DTMF decode and pager capabilities.

BC-167A/D WALL CHARGER
Charges the BP-227 in 12-13 hours (approx.). Same as supplied with some versions.

CS-V85 CLONING SOFTWARE + OPC-478/UC CLONING CABLE
Provides quick and easy programming of memory channel, names, etc. OPC-478UC is a USB cable type.

OPC-474 CLONING CABLE
Use for transceiver-to-transceiver data cloning.

FA-B2E VHF ANTENNA
Same as supplied.

MB-98 BELT CLIP
Alligator type clip. Same as supplied.

SP-13 EARPHONE
Provides clear audio even in noisy environments.

* Note: For European version, the silk printing on the front panel indicates "IC-V85" only.

Les spécifications et informations données dans ce document peuvent être modifiées sans préavis.

ICOM FRANCE

Zac de la Plaine - 1, Rue Brindejonc des Moulinais
BP 45804 - 31505 TOULOUSE CEDEX 5
Tél : 05 61 36 03 03 - Fax : 05 61 36 03 00
WEB ICOM : <http://www.icom-france.com>
E-mail : icom@icom-france.com



CACHET REVENDEUR

